

## E26 5" Trim Series

### DESCRIPTION

Open splay trim with self-flange and socket supporting bracket in the 5" trim family for use in recessed downlighting. Compatible for use in Halo and other housings.


Catalog #		Type
Project		
Comments		Date
Prepared by		

### SPECIFICATION FEATURES

- Splay trim for BR30 & PAR30 lamps
- Torsion spring retention
- Socket supporting integral bracket
- Self-flanged trim ring sized to hide gaps caused by construction tolerances

Housings	Max Lamp Compatibility
H5ICAT H5RICAT	
E5ICAT E5RICAT	60W PAR30S, 60W PAR30L, 50W BR30
H25ICAT	
H5ICATNB	
E5ICATNB	60W PAR30S, 60W PAR30L, 50W BR30
H25ICATNB	
H5T H5RT	75W PAR30S, 75W PAR30L, 65W BR30
E5TAT E5RTAT	
H5TNB	75W PAR30S, 75W PAR30L, 65W BR30
E5TATNB	

Compatible with Halogen, Incandescent, LED\* or CFL\* lamps.



### Dimensions:

A: 3-9/10" [99mm]  
 H: 4-4/5" [123mm]  
 OD: 6-5/8" [168mm]



**5186WH**  
White



**5186SN**  
Satin Nickel



**5186TBZ**  
Tuscan Bronze

## 5186

5-Inch Open Splay,  
Self-flange

### ORDERING INFORMATION

SAMPLE NUMBER: 5130WH

Trim	Finish
5186= 5" open splay, self-flange	WH=Matte White trim SN=Satin Nickel trim TBZ=Tuscan Bronze trim

### HALO HOUSING COMPATIBILITY

Trim #	Style	H5ICAT	H5RICAT	E5ICAT	E5RICAT	H25ICAT	H5ICATNB	E5ICATNB	H25ICATNB
5186	Splay	•	•	•	•	•	•	•	•
		H5T	H5RT	E5TAT	E5RTAT	H5TNB	E5TATNB		
		•	•	•	•	•	•		

For use in other's housings, refer to U.L. Classification list at [www.cooperlighting.com](http://www.cooperlighting.com)



For use in Halo listed housings.



Select trims are classified for use in others housings. See [www.cooperlighting.com](http://www.cooperlighting.com)

\*UL1993 listed LED & CFL equivalent lamps permitted. Consult lamp manufacturer for conditions of use. Cooper Lighting Solutions does not warranty the lamp.